



Description

The Levven Q Gateway connects the Levven controls and switches to the home network. Levven Q is how homeowners access and control every switch in their home from a mobile app on their device, or with voice commands to smart speakers in the home.

Installation

Place Levven Q in a central location, ideally near the Wi-Fi router or network switch. For optimum wireless reception, mount your Q vertically, high on a shelf or wall. Connect the supplied CAT-5 network cable between a LAN port on the home network router and Q's network port, and connect the Q to power.

Levven Q needs to be added to the controller group in the home. To group controllers yourself, refer to the guide at levven.com/support.

The Levven app is available on the Google Play Store and the Apple App Store. Search either store for "Levven". Follow the Levven Q Quick Start Guide for full step-by-step instructions.

Specifications:


Input Power	5V +/- 5%, 3A
Power consumption	Max 15W
Radio working frequency	902 to 928 MHz
Radio max power	20 dBm (100 mW)
Encryption	128-bit
Color	Grey
Enclosure rating	Indoor use only
Power rating	5V 3A US plug, 1m, cable black

Physical dimensions:

Height	125mm (4.9")
Width	105mm (4.1")
Depth	29mm (1.1")
Weight	250g (0.55lb)

Pairing

To add the Q Gateway to your home group, plug it in near the blue access wallplate and wait for the green light. Press the pairing button on the wallplate, then the V-shaped button on the Gateway. Both devices will flash red and green. Press the wallplate button again to confirm pairing, and both lights will turn solid green. The Q Gateway is now part of the group and ready for Wi-Fi connection.



Certifications for LC-Q2 Gateway:

FCC Part 15 Class B
FCC ID: 2AA9N-LCQ2
IC ID: ICES-3(B)/NMB-3(B)
Industry Canada ID: 11506A-LCQ2

Manufacturer information:
Levven Electronics Ltd.
9741 - 54 Ave NW
Edmonton, AB, Canada T6E 5J4

Proudly manufactured in 
Telephone: +1 (844)-553-8836
Email: info@levven.com
Website: www.levven.com



Presupuesto:

Potencia de Entrada	5V +/- 5%, 3A
Consumo de energía	Max 15W
Frecuencia de radio	902 a 928 MHz
Potencia máxima de radio	20 dBm (100 mW)
Cifrado	128-bit
Color	Gris
Clasificación de la carcasa	Solo para uso en interiores
Potencia nominal	Enchufe US 5V 3A, 1 m, cable negro

Dimensiones físicas:

Altura	125mm (4.9")
Ancho	105mm (4.1")
Profundidad	29mm (1.1")
Peso	250g (0.55lb)

Descripción

La Puerta de Enlace Levven Q conecta los controles e interruptores Levven a la red del hogar. Es la forma en que los propietarios acceden y controlan cada interruptor de su casa desde una app móvil o mediante comandos de voz a altavoces inteligentes.

Instalación


Coloca Levven Q en una ubicación central, idealmente cerca del router Wi-Fi o del switch de red. Para mejor recepción inalámbrica, monta el Q en posición vertical, en una repisa alta o en la pared. Conecta el cable de red CAT-5 incluido entre un puerto LAN del router y el puerto de red del Q, y enchúfalo a la corriente.

Levven Q debe añadirse al grupo de controladores del hogar. Para hacerlo tú mismo, consulta la guía en levven.com/support.

La app de Levven está disponible en Google Play y App Store. Busca "Levven" en cualquiera de las tiendas. Sigue la Guía Rápida de Levven Q para instrucciones completas paso a paso.

Emparejamiento

Para agregar la Gateway Q al grupo del hogar, conéctala cerca de la placa azul y espera la luz verde. Presiona el botón de vinculación en la placa, luego el botón en forma de "V" en la Gateway. Ambos parpadearán en rojo y verde. Presiona de nuevo el botón de la placa para confirmar; ambas luces quedarán en verde fijo. La Gateway Q ya está en el grupo y lista para conectarse al Wi-Fi.



Certificaciones para la Gateway LC-Q2:

FCC Parte 15 Clase B
FCC ID: 2AA9N-LCQ2
ID IC: ICES-3(B)/NMB-3(B)
ID Industria Canadá: 11506A-LCQ2

Información del fabricante:
Levven Electronics Ltd.
9741 - 54 Ave NW
Edmonton, AB, Canadá T6E 5J4

Fabricado con orgullo en 
Teléfono: +1 (844)-553-8836
Correo electrónico: info@levven.com
Sitio web: www.levven.com