



LC-Q2

Mobile Access Gateway Technical Specification Sheet



Description:

The Levven Q gateway connects the Levven controls and switches to the home network. Levven Q is how homeowners access and control every switch in their home from a mobile app on their device, or with voice commands to smart speakers in the home.

Installation:

Place Levven Q in a central location, ideally near the Wi-Fi router or network switch. For optimum wireless reception, mount your Q vertically, high on a shelf or wall. Connect the supplied CAT-5 network cable between a LAN port on the home network router and Q's network port, and connect the Q to power.

Levven Q needs to be added to the controller group in the home. To group controllers yourself, refer to the guide at levven.com/support.

The Levven app is available on the [Google Play Store](https://play.google.com/store/apps/details?id=com.levven) and the [Apple App Store](https://apps.apple.com/ca/app/levven/id1444444444). Search either store for "Levven". Follow the Levven Q [quick start guide](#) for full step-by-step instructions.

Specifications:

Input power	5V +/- 5%, 3A
Power consumption	Max 15W
Radio working frequency	902 to 928 MHz
Radio max power	20 dBm (100 mW)
Encryption	128-bit
Color	Grey
Enclosure rating	Indoor use only
Power adapter	5V 3A US plug, 1m cable, black

Certifications for LC-Q2 Gateway:


FCC Part 15 Class B
 FCC ID: 2AA9N-LCQ2
 IC: ICES-3(B)/NMB-3(B)
 Industry Canada ID: 11506A-LCQ2

Physical dimensions:

Height	125mm (4.9")
Width	105mm (4.1")
Depth	29mm (1.1")
Weight	250g (0.55 lb)

A product by [levven](#)

Levven Electronics Ltd
 9741 - 54 Ave
 Edmonton, Alberta T6E 5J4
 Canada

Proudly manufactured in 
 Telephone (780) 391-3000
<https://levven.com>

